



# ZXP399 DMX Controls and Accessories

## ZXP399 standalone controller 12V DMX

12 DC V - - Hz - Finger-protected - CE mark - Black

The ZXP399 DMX Controls and Wiring Accessories are to be used with our architectural and facade lighting luminaires (UniFlood C, M and G, UniStrip G4, UniEdge, UniDot G2, UniString and UniBar).;DMX Controls include a main controller, stand-alone controller, sub-controllers, DMX amplifier and DMX addressing device.;Main Controller: Industrial computer that can control up to 6,000 DMX universes.;Stand-alone Controller: Fits all medium applications with up to 700 DMX universes.;Wiring accessories include leader and jump cables with male and female IP67 connectors and end-caps.;Addressing Device: Hand-held device that can write DMX addresses to a whole run on-site within minutes.;DMX Amplifier: Compact, IP65 and low-power repeater that can amplify the DMX signal for up 100 metres.

### Product data

| General Information      |          |
|--------------------------|----------|
| CE mark                  | CE mark  |
| Colour                   | Black    |
| Operating and Electrical |          |
| Input Voltage            | 12 DC V  |
| Input frequency          | - Hz     |
| Mechanical and Housing   |          |
| Overall length           | 277.6 mm |

| Overall width                       | 193 mm                                  |
|-------------------------------------|---|
| Overall height                      | 66 mm                                   |
| Dimensions (height x width x depth) | 66 x 193 x 278 mm (2.6 x 7.6 x 10.9 in) |
| Approval and Application            |   |
| Ingress protection code             | IP20 [ Finger-protected]                |
| Product Data                        |   |
| Full product code                   | 911401756632                            |
| Order product name                  | ZXP399 standalone controller 12V DMX    |


## ZXP399 DMX Controls and Accessories

|                                   |              |
|-----------------------------------|--------------|
| Order code                        | 911401756632 |
| SAP numerator – quantity per pack | 1            |
| Numerator – packs per outer box   | 2            |
| SAP material                      | 911401756632 |

|                        |          |
|------------------------|----------|
| SAP net weight (piece) | 0.749 kg |
|------------------------|----------|



### Dimensional drawing



ZXP399

